



## Uses

The capacitors are applied to the compressor of air-conditioner, it assists for elector to start-up and run.

## Main features

- Small in dimension,high capacitance.
- Bear to the high voltage,low loss.
- Good self-healing character/
- Anti-explosive device and safety reliability.

## Technical specification

Reference Standard	GB3667-97、UL810、IEC60252	
Climatic category	40/85/21	
Rated voltage	250VAC~450VAC	
Capacitance Range	5~100 $\mu$ F	
Capacitance Tolerance	$\pm 5\%$ (j), $\pm 10\%$ (k)	
Test Voltage	T-T:1.5Un 1.75Un 25.60S 2.0Un	T-c: $\geq 2000$ VAC 2S. 60S
Dissipation Factor	$\leq 0.2\%$ (100Hz)	
Insulation Ristance	T-T: $\geq 3000$ M $\Omega \cdot \mu$ F	T-C: $\geq 1000$ M $\Omega$
Protection CIIass	P2 10,000AFC Protected	